




XXOJ	 ADATTATORE 90° ORIENTABILE JIC M BSP M	 ADAPTER ADJUSTABLE JIC M BSP M 90° ELBOW
	Adattatore 90° Orientabile M Gas - M JIC	BSP Male - JIC Male 90° Adjustable Adapter

	Quantità	codice	thread		L		H		E		Press.Max		NOTE
			T	T1	[in]	[mm]	[in]	[mm]	[in]	[mm]	[psi]	[bar]	
+	<input type="text"/>	74XXOJ0404	7/16-20	1/4-19	1,02	26	0,89	22,5	0,75	19	5511	380	-
+	<input type="text"/>	74XXOJ0405	1/2-20	1/4-19	1,24	31,5	1,06	27	0,75	19	5511	380	-
+	<input type="text"/>	74XXOJ0406	9/16-18	1/4-19	1,24	31,5	1,06	27	0,75	19	5511	380	-
+	<input type="text"/>	74XXOJ0606	9/16-18	3/8-19	1,44	36,5	1,12	28,5	0,87	22	5511	380	-
+	<input type="text"/>	74XXOJ0408	3/4-16	1/4-19	1,32	33,5	1,24	31,5	0,75	19	5511	380	-
+	<input type="text"/>	74XXOJ0608	3/4-16	3/8-19	1,42	36	1,24	31,5	0,87	22	5511	380	-
+	<input type="text"/>	74XXOJ0808	3/4-16	1/2-14	1,69	43	1,34	34	1,06	27	4931	340	-
+	<input type="text"/>	74XXOJ0810	7/8-14	1/2-14	1,69	43	1,44	36,5	1,06	27	4931	340	-
+	<input type="text"/>	74XXOJ1212	1.1/16-12	3/4-14	1,93	49	1,65	42	1,26	32	4061	280	-
+	<input type="text"/>	74XXOJ1216	1.5/16-12	3/4-14	1,81	46	2,05	52	1,26	32	2756	190	-
+	<input type="text"/>	74XXOJ1616	1.5/16-12	1-11	2,05	52	1,81	46	1,62	41	2756	190	-
+	<input type="text"/>	74XXOJ2020	1.5/8-12	1.1/4-11	2,25	57	2,05	52	1,97	50	2756	190	-
+	<input type="text"/>	74XXOJ2424	1.7/8-12	1.1/2-11	2,4	61	2,32	59	2,36	60	2611	180	-